

## Introduction

The Xilinx® LogiCORE™ IP Peak Cancellation - Crest Factor Reduction (PC-CFR) core is used to limit the dynamic range of the signals being transmitted in wireless communications and other applications.

## Additional Documentation

A product guide is available for this core. To request access to this material, click this registration link: [www.xilinx.com/member/pc\\_cfr\\_eval/index.htm](http://www.xilinx.com/member/pc_cfr_eval/index.htm).

## Features

- Support for multiple air interface standards.
- Smart Peak Processing mode for supporting wide transmit bandwidth up to 400 MHz, processes incoming samples at > 1.2 times instantaneous Bandwidth (iBW) reducing resource utilization.
- User selectable carrier configuration agnostic Window Crest Factor Reduction (WCFR) available as a standalone or a post processing stage.
- Support for power and frequency dynamics.
- Support for dynamic computation of Cancellation Pulse (CP).
- Support for optional hard clipper in post processing stage.
- Meets performance requirements (EVM, PAPR and ACLR) of all air interfaces.

For additional features see [Features \(cont.\)](#)

LogiCORE IP Facts Table	
Core Specifics	
Supported Device Family <sup>(1)</sup>	Zynq® UltraScale+™ RFSoc Family UltraScale™ Architecture Zynq® -7000 SoC 7 series FPGAs
Supported User Interfaces	AXI4-Stream, AXI4-Lite
Provided with Core	
Design Files	Encrypted RTL
Example Design	Not Provided
Test Bench	VHDL
Constraints File	Vivado XDC
Simulation Model	VHDL and Verilog Structural Simulation Model MATLAB® Model available
Supported S/W Driver	N/A
Tested Design Flows <sup>(2)</sup>	
Design Entry	Vivado® Design Suite
Simulation	For supported simulators, see the <a href="#">Xilinx Design Tools: Release Notes Guide</a> .
Synthesis	Vivado Synthesis
Support	
Provided by Xilinx @ <a href="http://www.xilinx.com/support">www.xilinx.com/support</a>	

### Notes:

1. For a complete listing of supported devices, see the Vivado IP catalog.
2. For the supported versions of the tools, see the [Xilinx Design Tools: Release Notes Guide](#).

## Features (cont.)

- Configurable clock-to-sample ratio of 1, 2, 3, 4, and 8.
- Configurable number of Cancellation Pulse Generators (CPGs) of 1 to 12 per iteration.
- Support for 1, 2, 4, 8, and 16 antennas.
- Support for 1 to 8 iterations.
- Quantization support for 16 and 18 bits.
- Support for cancellation pulse read back in static mode and base pulse read back in dynamic mode.
- Support for read back of CFR configuration and statistics registers.
- Support to work as a Stand-alone Hard Clipper.
- Optional feature to operate WCFR without smart peak processing.
- Support for data-path delay matched TUSER forwarding feature.
- A maximum of five different RATs are supported. The total number of carriers using all RATs is thirty. LTE 5 MHz and LTE 10 MHz are considered as different RATs because the corresponding base pulses are different.

## Overview

Crest Factor Reduction (CFR) is used to limit the dynamic range of the signals being transmitted in wireless communications and other applications. Multi-user and multi-carrier signals often have a high peak-to-average ratio (PAR). This places high demands on the data converters and especially limits the efficiency of operation of the Power Amplifiers (PAs) used in cellular base stations. Reducing the PAR is therefore beneficial in increasing PA efficiency by allowing higher average power to be transmitted before saturation occurs.

In a modern transmit chain, CFR is often incorporated with Digital Pre-distortion (DPD), which acts to linearize the PA, allowing operation at maximum efficiency with spectral compliance. CFR complements DPD because it levels the signal peaks, making accurate correction estimation easier.

The Xilinx PC-CFR core is an efficient, flexible, and easy-to-use implementation that supports Xilinx 7 series FPGAs, Zynq®-7000, Zynq UltraScale+™, and Zynq UltraScale+ RFSoc FPGAs. It is configurable both in function, supporting all major cellular wireless air interfaces, and in use, supporting many clocking and resource requirements. It can also handle dynamic power and frequency variations in the incoming data by computing the cancellation pulse coefficients dynamically.

---

## General Description

The PC-CFR core processes control and data through industry-standard AXI4 interfaces that allow immediate logic-free connection to other Xilinx IP components and to any general environment. The control interface is AXI4-Lite compliant and the data interface is AXI4-Stream compliant. The control interface provides access to a set of configuration registers and a pulse coefficient RAM and the data interface is used for streaming data in/out of the core. The data flow is unidirectional with no rate or bit-width change. A typical CFR application consists of multiple iterations and multiple antennas that can be configured through the Vivado Integrated Design Environment (IDE). The core is configured for a particular application through the control interface. In particular, the contents of the pulse coefficient RAM are related to the spectrum of the signal being transmitted. The *PC-CFR LogiCORE IP Product Guide* (PG097) documents how to produce these coefficients, and specific details are provided for the WCDMA, CDMA2000, WiMAX, TD-SCDMA, GSM, LTE, and 5G-NR air interfaces. Mixed-mode signal operation is also supported. Pulse coefficients can be pre-configured at generation time through a .coe file or configured in operation through the control interface. There is also provision for a shadow bank of coefficients to be loaded, and then activated with a select signal, to cater to applications where fast dynamic switching is required. Functions that can be run with MATLAB® are supplied for simulation and design of the cancellation pulse.

The core can be configured for clock-to-sample ratios between 1 and 8, and for algorithmic complexity, allowing FPGA resources to be minimized for a given application. The algorithmic complexity is the number of hardware resources available to cancel the signal peaks. These are called Cancellation Pulse Generators.

---

## Resource Requirements and Performance

The latest resource utilization and maximum clock frequency tables for various core configurations can be downloaded from PC-CFR evaluation lounge (registration required):

[http://www.xilinx.com/member/pc\\_cfr\\_eval/index.htm](http://www.xilinx.com/member/pc_cfr_eval/index.htm)

---

## Technical Support

Xilinx provides technical support at [www.xilinx.com/support](http://www.xilinx.com/support) for this LogiCORE IP product when used as described in the product documentation. Xilinx cannot guarantee timing, functionality, or support of product if implemented in devices that are not defined in the documentation, if customized beyond that allowed in the product documentation, or if changes are made to any section of the design labeled DO NOT MODIFY.

## Licensing and Ordering Information

This Xilinx LogiCORE IP module is provided under the terms of the [Xilinx Core License Agreement](#). The module is shipped as part of the Vivado Design Suite. For full access to all core functionalities in simulation and in hardware, you must purchase a license for the core. Contact your [local Xilinx sales representative](#) for information about pricing and availability.

For more information, visit the PC-CFR [product web page](#).

Information about other Xilinx LogiCORE IP modules is available at the [Xilinx Intellectual Property](#) page. For information on pricing and availability of other Xilinx LogiCORE IP modules and tools, contact your [local Xilinx sales representative](#).

## Evaluation

An evaluation license is available for this core. The evaluation version operates in the same way as the full version for several hours, dependent on clock frequency. Allocation of the cancellation pulse generators is then completely disabled, and the data output comprises a delayed version of the data input. If you notice this behavior in hardware, it probably means you are using an evaluation version of the core. The Xilinx tools warn that an evaluation license is being used during netlist implementation. If a full license is installed, delete the old XCO file, reconfigure and regenerate the core. More details on evaluation can be found in the PC-CFR evaluation lounge (registration required): [http://www.xilinx.com/member/pc\\_cfr\\_eval/index.htm](http://www.xilinx.com/member/pc_cfr_eval/index.htm).

## Revision History

The following table shows the revision history for this document.

Date	Version	Description of Revisions
01/08/2021	6.4	Extended the LUT optimization features available for CPS=2 in PC-CFR v6.3 to <i>all</i> CPS cases. These optimizations must be seen in all smart peak processing cases.
05/22/2019	6.3	Enabled LUT optimization for SPP and Data Rate (clock-cycles/samples) = 2 scenarios at the cost of 3 DSP48s increase per iteration.
12/05/2018	6.2	Updated the Features section with a description of Dynamic mode.
06/20/2018	6.2	<ul style="list-style-type: none"> <li>Added 16 antenna support.</li> <li>DSP48 optimization in CPGs.</li> <li>Core is fully supported in Vivado 2018.2.</li> </ul>

Date	Version	Description of Revisions
10/05/2016	6.1	<ul style="list-style-type: none"> <li>Added support to work as Stand-alone Hard Clipper.</li> <li>Added optional feature to operate WCFR without smart peak processing.</li> <li>Added TUSER forwarding feature.</li> <li>Added Support for two more RATs (RATD and RATE) in dynamic CP computation mode.</li> </ul>
11/18/2015	6.0	Added support for UltraScale+ families.
04/01/2015	6.0	Production release of PC-CFR v6.0 core.
10/01/2014	6.0	<ul style="list-style-type: none"> <li>Version 6.0 is Early Access, Lounge delivered to customers.</li> <li>Added UltraScale Architecture support.</li> <li>Updated Features.</li> <li>Removed resource table and replaced with link to product page.</li> </ul>
12/18/2013	5.0	<ul style="list-style-type: none"> <li>Revision number advanced to 5.0 to align with core version number.</li> <li>Added dynamic support (dynamic power variation and frequency hopping)</li> <li>Hard clipper support</li> <li>Change in tool settings for characterization</li> <li>New TUSER port added in Dynamic mode</li> </ul>
03/20/2013	3.0	PC-CFR v4.0 is available only with Vivado; other changes are <ul style="list-style-type: none"> <li>Improved <math>f_{max}</math>, core can be clocked at 491.52 MHz for -2 devices</li> <li>Core latency has changed</li> </ul>
12/18/2012	2.0	Updated for 2012.4/14.4. <ul style="list-style-type: none"> <li>Real/Complex CP selection added</li> <li>Number of CPGs/iteration increased to 12</li> <li>Core is fully supported in Vivado 2012.4</li> <li>Peak detect window is used in place of allocator spacing</li> </ul>
06/22/2011	1.0	Initial Xilinx release. Previous version of this Product Brief is XMP039.

## Please Read: Important Legal Notices

The information disclosed to you hereunder (the "Materials") is provided solely for the selection and use of Xilinx products. To the maximum extent permitted by applicable law: (1) Materials are made available "AS IS" and with all faults, Xilinx hereby DISCLAIMS ALL WARRANTIES AND CONDITIONS, EXPRESS, IMPLIED, OR STATUTORY, INCLUDING BUT NOT LIMITED TO WARRANTIES OF MERCHANTABILITY, NON-INFRINGEMENT, OR FITNESS FOR ANY PARTICULAR PURPOSE; and (2) Xilinx shall not be liable (whether in contract or tort, including negligence, or under any other theory of liability) for any loss or damage of any kind or nature related to, arising under, or in connection with, the Materials (including your use of the Materials), including for any direct, indirect, special, incidental, or consequential loss or damage (including loss of data, profits, goodwill, or any type of loss or damage suffered as a result of any action brought by a third party) even if such damage or loss was reasonably foreseeable or Xilinx had been advised of the possibility of the same. Xilinx assumes no obligation to correct any errors contained in the Materials or to notify you of updates to the Materials or to product specifications. You may not reproduce, modify, distribute, or publicly display the Materials without prior written consent. Certain products are subject to the terms and conditions of Xilinx's limited warranty, please refer to Xilinx's Terms of Sale which can be viewed at <http://www.xilinx.com/legal.htm#tos>; IP cores may be subject to warranty and support terms contained in a license issued to you by Xilinx. Xilinx products are not designed or intended to be fail-safe or for use in any application requiring fail-safe performance; you assume sole risk and liability for use of Xilinx products in such critical applications, please refer to Xilinx's Terms of Sale which can be viewed at <http://www.xilinx.com/legal.htm#tos>.

### AUTOMOTIVE APPLICATIONS DISCLAIMER

AUTOMOTIVE PRODUCTS (IDENTIFIED AS "XA" IN THE PART NUMBER) ARE NOT WARRANTED FOR USE IN THE DEPLOYMENT OF AIRBAGS OR FOR USE IN APPLICATIONS THAT AFFECT CONTROL OF A VEHICLE ("SAFETY APPLICATION") UNLESS THERE IS A SAFETY CONCEPT OR REDUNDANCY FEATURE CONSISTENT WITH THE ISO 26262 AUTOMOTIVE SAFETY STANDARD ("SAFETY DESIGN"). CUSTOMER SHALL, PRIOR TO USING OR DISTRIBUTING ANY SYSTEMS THAT INCORPORATE PRODUCTS, THOROUGHLY TEST SUCH SYSTEMS FOR SAFETY PURPOSES. USE OF PRODUCTS IN A SAFETY APPLICATION WITHOUT A SAFETY DESIGN IS FULLY AT THE RISK OF CUSTOMER, SUBJECT ONLY TO APPLICABLE LAWS AND REGULATIONS GOVERNING LIMITATIONS ON PRODUCT LIABILITY.