

Introduction

The IEEE 802.16e CTC decoder core performs iterative decoding of channel data that has been encoded as described in Section 8.4.9.2.3 of the IEEE Std 802.16e-2005 specification and corrigendum IEEE P802.16Rev2/D0b (June 2007). The IEEE 802.16e code is a parallel concatenated convolutional code with an input data block of 2N bits. Through parallel processing with parameterizable number of SISOs, this LogiCORE™ IP decoder core is capable of achieving high throughput. The decoded data rate reaches up to 220 Mbps with five iterations using eight SISOs at 286 MHz clock frequency.

Features

- Supports Virtex®-6, Virtex-5, Virtex-4, Spartan®-6, Spartan-3, Spartan-3E, and Spartan-3A DSP FPGA families
- Supports all interleaver block sizes of the CTC OFDMA PHY mode including the HARQ and IR HARQ modes: 24, 36, 48, 72, 96, 108, 120, 144, 180, 192, 216, 240, 480, 960, 1440, 1920, and 2400 pairs
- Performs parallel processing with parameterizable number of SISOs to achieve high throughput and reduce latency
- Supports dynamic block size switching without interruption
- Programmable number of iterations dynamically changeable per block
- Adaptive rate change via puncturing interface
- Uses MAX-LOG-MAP algorithm with extrinsic scaling
- Parameterizable options for soft data input and extrinsic bits
- Clock speed exceeds 162 MHz in Virtex-4 speed grade -10, 196 MHz in Virtex-5 speed grade -1, and 225 MHz in Virtex-6 speed grade -1
- Decoded data rate depends on block size and varies between 44 Mbps to 63 Mbps when targeting Virtex-4, between 53 Mbps to 76 Mbps when targeting Virtex-5, and between 61 Mbps to

88 Mbps when targeting Virtex-6 (slowest speed grade, five iterations, and four SISO option)

- Latency depends on block size and varies between 5 μ s to 76 μ s when targeting Virtex-4, between 4 μ s to 63 μ s when targeting Virtex-5, and between 4 μ s to 55 μ s when targeting Virtex-6 (slowest speed grade, five iterations, and four SISO option)
- Fully synchronous design with single clock domain
- Double-buffered input to accommodate burst or continuous data
- Available using the CORE Generator™ v11.2 software, which is included with the ISE® 11.2 software

LogiCORE™ Facts	
Core Specifics	
Supported Device Family	Virtex®-4, Virtex-5, Virtex-6, Spartan®-3, Spartan-3E, Spartan-3A DSP, Spartan-6
Resources Used	See Resource Utilization: Table 9 through Table 12 in the Data Sheet
Provided with Core	
Documentation	Data Sheet (DS634)
Design File Formats	NGC netlist and VHDL or Verilog Simulation Model
Constraints File	UCF
Verification	VHDL Test Bench
Instantiation Template	VHDL Wrapper
Design Tool Requirements	
Xilinx Implementation Tools	ISE 11.2
Verification	ModelSim PE 6.2c
Simulation	ModelSim PE 6.2c
Synthesis	XST
Support	
Provided by Xilinx, Inc.	

Ordering Information

Disclaimer: France Telecom, for itself and certain other parties, claims certain intellectual property rights covering Turbo Codes technology, and has decided to license these rights under a licensing program called the Turbo Codes Licensing Program. Supply of this IP core does not convey a license nor imply any right to use any Turbo Codes patents owned by France Telecom, TDF or GET. Contact France Telecom for information about its Turbo Codes Licensing Program at the following address:

France Telecom R&D
 VAT/TURBOCODES
 38, rue du Général Leclerc
 92794 Issy Moulineaux
 Cedex 9
 France

The IEEE 802.16e CTC Decoder core is provided under the [SignOnce IP Site License](#) and can be generated using the Xilinx ISE CORE Generator v11.2 or higher. The CORE Generator software is shipped with Xilinx ISE Foundation™ Series Development software.

To access the full functionality of the core, including simulation and FPGA bitstream generation, a full license must be obtained from Xilinx. For more information, visit the [IEEE 802.16e CTC Decoder Product Page](#).

Contact your local Xilinx [sales representative](#) for more information, including the full decoder data sheet, licensing, pricing and availability on Xilinx LogiCORE™ IP products and software.

Revision History

The following table shows the revision history for this document:

Date	Version	Description of Revisions
10/10/07	1.0	Initial Xilinx release.
06/24/09	2.0	Updated for core v4.0.
12/02/09	2.1	ISE version numbers revised.

Notice of Disclaimer

Xilinx is providing this product documentation, hereinafter “Information,” to you “AS IS” with no warranty of any kind, express or implied. Xilinx makes no representation that the Information, or any particular implementation thereof, is free from any claims of infringement. You are responsible for obtaining any rights you may require for any implementation based on the Information. All specifications are subject to change without notice. XILINX EXPRESSLY DISCLAIMS ANY WARRANTY WHATSOEVER WITH RESPECT TO THE ADEQUACY OF THE INFORMATION OR ANY IMPLEMENTATION BASED THEREON, INCLUDING BUT NOT LIMITED TO ANY WARRANTIES OR REPRESENTATIONS THAT THIS IMPLEMENTATION IS FREE FROM CLAIMS OF INFRINGEMENT AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Except as stated herein, none of the Information may be copied, reproduced, distributed, republished, downloaded, displayed, posted, or transmitted in any form or by any means including, but not limited to, electronic, mechanical, photocopying, recording, or otherwise, without the prior written consent of Xilinx.