

Introduction

The LogiCORE™ IP SelectIO™ Interface Wizard simplifies the integration of the SelectIO technology into the system design in the Spartan®-6 and lower-power Spartan-6 devices, and the Kintex™-7, Virtex-7 and Virtex®-6 and low power Virtex-6 devices. The Wizard creates an HDL file (Verilog or VHDL) that instantiates and configures I/O logic such as Input SERDES, Output SERDES and DELAY blocks configured to customer requirements. Additionally, it instantiates and configures the desired I/O clock primitive, connecting to the instantiated I/O logic.

Features

- Supports input, output or directional busses
- Creates clock circuitry required to drive I/O logic
- Supports up to a 16-bit wide data bus
- Supports optional data serialization for each FPGA family
- Supports optional data and/or clock delay insertion
- Supports single and double data rate data
- Templates include support for configuring the data buses of the following: Chip-to-Chip, Camera receiver, Camera transmitter, DVI receiver, DVI transmitter and SGMII
- Implements phase detector functionality for Spartan-6 FPGA designs
- Output can be pulled into PlanAhead™ design tool for further I/O attribute setting
- Provides synthesizable example design and demonstration test bench to help with integration

LogiCORE IP Facts Table					
Core Specifics					
Supported Device Family ⁽¹⁾	Kintex-7 ⁽²⁾ , Virtex-6 ⁽³⁾ Virtex-7 ⁽²⁾ , Spartan-6 ⁽⁴⁾				
Supported User Interfaces	None				
	Resources ⁽⁵⁾				Frequency
	LUTs	FFs	DSP Slices	Block RAMs	Max. Freq.
	82	0-68	N/A	N/A	N/A
Provided with Core					
Documentation	Product Specification Getting Started Guide				
Design Files	Verilog and VHDL				
Example Design	Verilog and VHDL				
Test Bench	VHDL, Verilog				
Constraints File	User Constraints File				
Simulation Model	None				
Tested Design Tools					
Design Entry Tools	ISE 13.1 CORE Generator tool				
Simulation	ISim 13.1 Mentor Graphics ModelSim 6.6d Cadence IES 10.2 Synopsys VCS and VCS MX 2010.06				
Synthesis Tools	XST 13.1 Synopsys Synplify PRO E-2011.03				
Support					
Provided by Xilinx, Inc.					

1. For a complete listing of supported devices, see the release notes for this Wizard.
2. For more information on the Kintex-7 and Virtex-7 devices, see the *7 Series FPGAs Overview* [Ref 4].
3. For more information on the Virtex-6 devices, see the *Virtex-6 Family Overview* [Ref 3].
4. For more information on the Spartan-6 devices, see the *Spartan-6 Family Overview* [Ref 1].
5. These are the maximum resources used when phase detector is implemented.

Support

Xilinx provides technical support for this LogiCORE IP product when used as described in the product documentation. Xilinx cannot guarantee timing, functionality, or support of product if implemented in devices that are not defined in the documentation, if customized beyond that allowed in the product documentation, or if changes are made to any section of the design labeled DO NOT MODIFY.

Ordering Information

The SelectIO Interface Wizard LogiCORE IP core is provided free of charge under the terms of the [Xilinx End User License Agreement](#). The core can be generated by the Xilinx® ISE CORE Generator™ software, which is a standard component of the Xilinx ISE Design Suite. This version of the core can be generated using the ISE CORE Generator system. For more information, please visit the [Architecture Wizards web page](#).

Information about additional Xilinx LogiCORE modules is available at the [Xilinx IP Center](#). For pricing and availability of other Xilinx LogiCORE modules and software, please contact your local Xilinx [sales representative](#).

References

1. [DS160](#): *Spartan-6 Family Overview*
2. [UG700](#): *LogiCORE IP SelectIO Interface Wizard Getting Started Guide*
3. [DS150](#): *Virtex-6 Family Overview*
4. [DS180](#): *7 Series FPGAs Overview*

Revision History

The following table shows the revision history for this document:

Date	Version	Description of Revisions
09/16/09	1.1	Initial Xilinx release.
12/02/09	1.2	Added Spartan-6 -1L (Lower Power) device support.
04/19/10	1.3	Updated Wizard and tools. Added Resources Used rows in the Facts table, "Support" and "Ordering Information."
07/23/10	1.4	Revised LogiCORE IP Facts table's format and content. Added support for Virtex-6 devices.
03/01/11	2.0	Updated for core v3.1 and Xilinx tools v13.1.

Notice of Disclaimer

Xilinx is providing this product documentation, hereinafter “Information,” to you “AS IS” with no warranty of any kind, express or implied. Xilinx makes no representation that the Information, or any particular implementation thereof, is free from any claims of infringement. You are responsible for obtaining any rights you may require for any implementation based on the Information. All specifications are subject to change without notice. XILINX EXPRESSLY DISCLAIMS ANY WARRANTY WHATSOEVER WITH RESPECT TO THE ADEQUACY OF THE INFORMATION OR ANY IMPLEMENTATION BASED THEREON, INCLUDING BUT NOT LIMITED TO ANY WARRANTIES OR REPRESENTATIONS THAT THIS IMPLEMENTATION IS FREE FROM CLAIMS OF INFRINGEMENT AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Except as stated herein, none of the Information may be copied, reproduced, distributed, republished, downloaded, displayed, posted, or transmitted in any form or by any means including, but not limited to, electronic, mechanical, photocopying, recording, or otherwise, without the prior written consent