



100% Material Declaration Data Sheet FFG1156

PK397 (v1.1.1) July 22, 2011

Average Weight: 11.0927g

Component	Substance Description	CAS Number or Description	Percentage of Component	Use in Product	Component Weight/ Substance Weight (grams)	Component Percent of Total
Silicon Die (FPGA)				Silicon IC	0.77363	6.974
	Doped silicon	7440-21-3	100.00	Basis	0.77363	
Solder Bump				Die to package	0.258210	2.328
	Tin (Sn)	7440-31-5	63.00	Basis	0.162672	
	Lead (Pb)	7439-92-1	37.00	Basis	0.095538	
Die Underfill					0.130000	1.172
	Bisphenol F-type liquid epoxy resin	9003-36-5	15.00	Basis	0.019500	
	Phenolic resin	Trade secret	15.00	Basis	0.019500	
	Bisphenol A-type liquid epoxy resin	25068-38-6	5.00	Basis	0.006500	
	Amine type accelerator	Trade secret	5.00	Basis	0.006500	
	Silicon dioxide	60676-86-0	54.00	Basis	0.070200	
	Carbon black	1333-86-4	1.00	Basis	0.001300	
	Additives	Trade secret	5.000	Basis	0.006500	
Heat Spreader					4.989300	44.978
	Copper (Cu)	7440-50-8	98.65	Main material	4.921944	
	Nickel (Ni)	7440-02-0	1.35	Main material	0.067356	
Heat Spreader Adhesive					0.152000	1.370
	Organopolysiloxane mixture	N/A	100.00	Main material	0.152000	
Solder Balls					0.965679	8.706
	Tin (Sn)	7440-31-5	95.50	Main material	0.922224	
	Silver (Ag)	7440-22-4	4.00	Main material	0.038627	
	Copper (Cu)	7440-50-8	0.50	Main material	0.004828	
Capacitor					0.041280	0.372
	Ceramic (BaTiO ₃)	N/A	61.80	Ceramic	0.025511	
	Inner electrode (Ni)	7440-02-0	27.00	Inner electrode	0.011146	
	Outer electrode (Cu)	7440-50-8	9.90	Outer electrode	0.004087	
	Plating 1 (Ni)	7440-02-0	0.40	Plating1	0.000165	
	Plating 2 (Sn)	7440-31-5	0.90	Plating2	0.000372	

© Copyright 2011 Xilinx, Inc. XILINX, the Xilinx logo, Virtex, Spartan, ISE, and other designated brands included herein are trademarks of Xilinx in the United States and other countries. All other trademarks are the property of their respective owners

Component	Substance Description	CAS Number or Description	Percentage of Component	Use in Product	Component Weight/ Substance Weight (grams)	Component Percent of Total
Capacitor					0.039600	0.357
	Ceramic (BaTiO ₃)	N/A	67.40	Ceramic	0.026690	
	Inner electrode (Ni)	7440-02-0	17.00	Inner electrode	0.006732	
	Outer electrode (Cu)	7440-50-8	13.80	Outer electrode	0.005465	
	Plating 1 (Ni)	7440-02-0	0.50	Plating1	0.000198	
	Plating 2 (Sn)	7440-31-5	1.30	Plating2	0.000515	
Ink					Trace	Trace
	2-Butoxyethanol	111-76-2	Trace	Basis	Trace	
	Benzylalcohol	100-51-6	Trace	Basis	Trace	
	Isobutanol	78-83-1	Trace	Basis	Trace	
	Xylene	1330-20-7	Trace	Basis	Trace	
	Bisphenol	25068-38-6	Trace	Basis	Trace	
Substrate					3.743	33.743
Plating	Copper	7440-50-8	37.54	Main material	1.405	
	Nickel	7440-02-0	0.61	Main material	0.023	
	Gold	7440-57-5	0.19	Main material	0.007	
Bump	Lead	7439-92-1	0.48	Main material	0.018	
	Tin	7440-31-5	0.83	Main material	0.031	
Core	Bismaleimide	13676-54-5	13.36	Main material	0.500	
	Triazine	25722-66-1	13.36	Main material	0.500	
	Epoxy resin	29690-82-2 68541-56-0 25068-38-6	4.01	Main material	0.150	
	Inorganic filler	13776-74-4/7631	0.45	Main material	0.017	
	Fiberglass	65997-17-3	13.36	Main material	0.500	
ABF	Bisphenol A-type epoxy resin	25068-38-6	3.93	Main material	0.147	
	Cyclohexane	108-94-1	3.93	Main material	0.147	
	N, N-dimethylformamide	68-12-2	3.93	Main material	0.147	
	Silica powder (Silicon dioxide)	7631-86-9	3.93	Main material	0.147	
Solder Mask	Solder mask	N/A	0.11	Main material	0.0040	

Revision History

The following table shows the revision history for this document.

Date	Version	Description of Revisions
11/02/09	1.0	Initial Xilinx release.
08/03/10	1.1	Updated average weight. Updated component percentage of total for all components. Added substances and corresponding data to ink and substrate components.
07/22/11	1.1.1	Change CAS# for N, N-dimethylformamide from 68-12-1 to 68-12-2

Notice of Disclaimer

Xilinx regards this materials data to be correct but makes no guarantee as to its accuracy or completeness, including, but not limited to, with respect to its compliance with applicable environmental laws and regulations. Xilinx subcontracts the production, test and assembly of hardware devices to independent third-party vendors and materials suppliers (“Contractors”). All data provided hereunder is based on information received from Contractors. Xilinx has not independently verified the accuracy or completeness of this information which is provided solely for your reference in connection with the use of Xilinx products.